

Multi Super DC Inverter

Tabuľky kombinovateľnosti

M2OH-14HFN8-Q(B)	1 vnút.j.	2 vnút.j.	M2OE-18HFN8-Q(B)	1 vnút.j.	2 vnút.j.	M3OG-21HFN8-Q(B)	1 vnút.j.	2 vnút.j.	3 vnút.j.
	9	9 + 9		9	9 + 9		9	9 + 9	9 + 9 + 9
	12	9 + 12		12	9 + 12		12	9 + 12	—
	18	—		18	12 + 12		18	9 + 18	—

M3OA-27HFN8-Q(B)	1 vnútorná jednotka	2 vnútorné jednotky		3 vnútorné jednotky	
	9	9 + 9	12 + 12	9 + 9 + 9	9 + 12 + 12
	12	9 + 12	12 + 18	9 + 9 + 12	12 + 12 + 12
	18	9 + 18	—	9 + 12 + 12	—

M4OE-28HFN8-Q(B)	1 vnútorná jednotka	2 vnútorné jednotky	3 vnútorné jednotky	4 vnútorné jednotky
	9	9 + 9 12 + 18	9 + 9 + 9	9 + 9 + 9 + 9
	12	9 + 12 12 + 24	9 + 9 + 12	—
	18	9 + 18 18 + 18	9 + 9 + 18	—
	24	9 + 24 —	9 + 12 + 12	—
	—	12 + 12 —	12 + 12 + 12	—

M4O-36FN8-Q(B)	1 vnútorná j.	2 vnútorné jednotky	3 vnútorné jednotky	4 vnútorné jednotky
	9	9 + 9 18 + 18	9 + 9 + 9 9 + 18 + 18	9 + 9 + 9 + 9 12 + 12 + 12 + 12
	12	9 + 12 —	9 + 9 + 12 12 + 12 + 12	9 + 9 + 9 + 12 12 + 12 + 12 + 18
	18	9 + 18 —	9 + 9 + 18 12 + 12 + 18	9 + 9 + 9 + 18 —
	24	9 + 24 —	9 + 9 + 24 12 + 12 + 24	9 + 9 + 12 + 12 —
	—	12 + 12 —	9 + 12 + 12 12 + 18 + 18	9 + 9 + 12 + 18 —
	—	12 + 18 —	9 + 12 + 18 —	9 + 12 + 12 + 12 —
	—	12 + 24 —	9 + 12 + 24 —	9 + 12 + 12 + 18 —

M5OE-42HFN8-Q(B)	1 vnút.j.	2 vnút.j.	3 vnútorné jednotky	4 vnútorné jednotky	5 vnútorných jednotiek
	9	9 + 9	9 + 9 + 9 12 + 12 + 12	9 + 9 + 9 + 9 12 + 12 + 12 + 12	9 + 9 + 9 + 9 + 9 12 + 12 + 12 + 12 + 12
	12	9 + 12	9 + 9 + 12 12 + 12 + 18	9 + 9 + 9 + 12 12 + 12 + 12 + 18	9 + 9 + 9 + 9 + 12 —
	18	9 + 18	9 + 9 + 18 12 + 12 + 24	9 + 9 + 9 + 18 —	9 + 9 + 9 + 9 + 18 —
	24	9 + 24	9 + 9 + 24 12 + 18 + 18	9 + 9 + 9 + 24 —	9 + 9 + 9 + 12 + 12 —
	—	12 + 12	9 + 12 + 12 —	9 + 9 + 12 + 12 —	9 + 9 + 9 + 12 + 18 —
	—	12 + 18	9 + 12 + 18 —	9 + 9 + 12 + 18 —	9 + 9 + 12 + 12 + 12 —
	—	12 + 24	9 + 12 + 24 —	9 + 12 + 12 + 12 —	9 + 12 + 12 + 12 + 12 —
	—	18 + 18	9 + 18 + 18 —	9 + 12 + 12 + 18 —	9 + 12 + 12 + 12 + 18 —